Panasonic KX-TGP500 Admin Guide





How To Find The IP Address

- 1. Press the "Menu" button on a handset (Center Joystick).
- 2. Press the following key presses on the keypad ([#][5][3][4]).
- 3. Select "On" for "Embedded web" [SAVE].
- 4. Now to view the IP Address press the "Menu" button on a handset (center of joystick).

How To Find The MAC Address

Quick Steps

1. First log into the Web Admin GUI of the phone.

	Authentication Required
?	A username and password are being requested by http://10.10.0.225. The site says: "Authorization"
User Name:	admin
Password:	••••
	Cancel

2. Click on "Network Status" option on the left side

Panasonic							
KX-TGP500B04	Status	Network	System	VoIP	Telephone	Maintenance	
Web Port Close			Versio	n Info	rmation		
Status	Version In	formation					
Version Information	Model			KX-TG	P500B04		
VolP Status	Operatio	ng BANK		Bank1			
	IPL Vers	sion		01.02			
	Firmwa	o Vorsion		Bank1	: 12.58		
	FIIIIWa	e version		Bank2	: 12.17		

3. The MAC address will be displayed like below

Panasonic						
KX-TGP500B04	Status	Network	System	VolP	Telephone	Maintenance
Web Port Close			Netv	vork S	tatus	Refresh
Status	Network S	tatus				
Version Information	MAC A	ddress		0080F	0B6E801	
Network Status	Etherne	t Link Status	(LAN Port)	Conne	cted	
	Connec	tion Mode		DHCP		
	IP Addr	ess		10.10.0	0.225	
	Subnet	Mask		255.25	5.255.0	
	Default	Gateway		10.10.0	0.254	
	DNS1			199.10	2.239.4	
	DNS2					

How To Set The Configuration Server

Quick Steps

1. First log into the Web Admin GUI of the phone.

	Authentication Required
	A username and password are being requested by http://10.10.0.225. The site says: "Authorization"
User Name:	admin
Password:	••••
	Cancel OK

2. Next select the "Maintenance" tab at the top right.

Panasonic							
KX-TGP500B04	Status	Network	System	VolP	Telephone	Maintenance	
Web Port Close	-		Versio	n Info	rmation		
Status	Version Infor	rmation					
Version Information	Model			KX-TG	P500B04		
VoIP Status	Operating	BANK		Bank1			
	IPL Version	n		01.02			
	Eirmwaro	Vorsion		Bank1	: 12.58		
	Firmware	version		Bank2	: 12.17		

3. Next select the "Provisioning Maintenance" tab.

Panasonic						
KX-TGP500B04	Status	Network	System	VolP	Telephone	Maintenance
Web Port Close			Firmwa	are Ma	intenance	
Maintenance	Firmware	Maintenand	e			
Firmware Maintenance	Enable	Firmware U	pdate	• Yes	○ No	
Provisioning Maintenance	Update	Туре		 Auto 	matic O Manual	
Management Server	Firmwa	re File URL		tftp://10.	10.0.1/panasonic/2,	TGP500.fw
Reset to Defaults						
Restart				Save	Cancel	

4. You can now specify the provisioning server information. In our example we are using tftp://10.10.0.1/Config{MAC}.cfg

Panasonic		
KX-TGP500B04	Status Network System	VoIP Telephone Maintenance
Web Port Close	Provisio	ning Maintenance
Maintenance	Provisioning Maintenance	
Firmware Maintenance	Enable Provisioning	⊙ Yes ○ No
Provisioning Maintenance	Standard File URL	tftp://10.10.0.1/Config{MAC}.cfg
Management Server	Product File URL	
Reset to Defaults	Master File URL	
Restart	Cyclic Auto Resync	○ Yes ⊙ No
	Resync Interval	10080 minute(s) [1-40320]
	Header Value for Resync Event	check-sync
		Save Cancel

How To Factory Default

Quick Steps

1. First log into the Web Admin GUI of the phone.

	Authentication Required
2	A username and password are being requested by http://10.10.0.225. The site says: "Authorization"
User Name:	admin
Password:	••••
	Cancel

2. Next select the "Maintenance" Tab at the top right.

Panasonic							
KX-TGP500B04	Status	Network	System	VoIP	Telephone	Maintenance	
Web Port Close			Versio	n Info	rmation		_
Status	Version In	formation					
Version Information	Model			KX-TO	GP500B04		
VolP Status	Operati	ng BANK		Bank1			
	IPL Ver	sion		01.02			
	Firmura			Bank1	: 12.58		
	Filliwa	re version		Bank2	:: 12.17		

3. Now use the left navigation menu to select "Reset To Defaults".

Panasonic		
KX-TGP500B04	Status Network System	VoIP Telephone Maintenance
Web Port Close	Firmw	vare Maintenance
Maintenance	Firmware Maintenance	
Firmware Maintenance	Enable Firmware Update	⊙ Yes ◯ No
Provisioning Maintenance	Update Type	 ● Automatic ○ Manual
Management Server	Firmware File URL	tftp://10.10.0.1/panasonic/2/TGP500.fw
Reset to Defaults		
Restart		Save Cancel

4. Finally click "Reset Web Settings" to complete the reset.

Panasonic						
KX-TGP500B04	Status	Network	System	VolP	Telephone	Maintenance
Web Port Close			Rese	et to De	efaults	
Maintenance	Reset We	b Data				
Firmware Maintenance Local Firmware Update Provisioning Maintenance	The We [Reset	eb data for th Web Settings	is unit will be s].	reset to i	ts default values	when you click
Management Server Reset to Defaults			R	eset Web Se	ttings	
Restart						



(920) 886-8130

http://schmoozecom.com