# Panasonic KX-UT670 Admin Guide





### How To Find IP Address & MAC Address

#### **Quick Steps**

1. Press the "Menu" button.



2. Press the "Settings" button.



3. Scroll down and press the "About Phone" option.



4. Select the "Status" option.

▲ ∩ ♥ • ← ≅	4706 UT670	
About phone		
Status Network, Service state, etc.		
Legal information		
Model number KX-UT670		
OS Version		
Kernel version		
Firmware version		

5. The IP address and MAC address will be displayed.

About phone Status Network, Service state ste Legal i Network OK (10.4.0.152)	
Status       Network, Septementation       Legal in       Network       OK (10.4.0.152)	
Legal i Network OK ( 10.4.0.152 )	
Network OK (10.4.0.152)	
Model	
OS Ver	
<sup>2.2</sup> MAC address 00:00:00:00:00	
2.6.32.9 OK	
Firmware version	

## How To Set the Configuration Server

#### **Quick Steps**

1. Log into the Web Admin GUI of the phone.

?	Authentication Required A username and password are being requested by http://10.4.0.152. The site says: "Authorization"							
User Name: Password:								
	Cancel OK							

2. Select the "Maintenance" tab at the top right.

Panasonic							
KX-UT670	Status	Network	System	VoIP	Telephone	Maintena	ance
Web Port Close			Versio	n Infoi	rmation		
Status	Version In	formation					
Version Information	Model			KX-UT	670		
Network Status	OS Ver	sion		2.2			
VolP Status	Firmware Version			01.072	01.072		

3. Next select "Provisioning Maintenance".

Р	an	as	or	nic
	-			

relephone Maintenance								
Firmware Maintenance								
No								
http://10.10.0.1:2004/panasonic/2/UT670.bin								
Cancel								
1								

4. You can now specify the provisioning server information. In our example we are using tftp://10.10.0.1/Config{MAC}.cfg

Panasonic									
KX-UT670	Status	Network	System	VolP	Telephone	Maintenance			
Web Port Close		Provisioning Maintenance							
Maintenance	Provision	ing Maintena	ince						
Firmware Maintenance	Enable	Provisioning	⊙ Yes ⊖ N	lo					
Provisioning Maintenance Reset to Defaults	Standard File URL		http://10.10.0.1:2004/Config{MAC}.cfg						
Restart	Product	File URL							
	Master I	File URL							
	Cyclic A	uto Resync	🔾 Yes 💿 N	lo					
	Resync	Interval	10080	minute(s)	[1-40320]				
	Header Value for Resync Event check-sync								
	Save Cancel								

## How To Factory Default

#### **Quick Steps**

1. Log into the Web Admin GUI of the phone

?	Authentication Required A username and password are being requested by http://10.4.0.152. The site says: "Authorization"							
User Name:								
Password:								
	Cancel OK							

2. Next select the "Maintenance" tab at the top right.

Panasonic							
KX-UT670	Status	Network	System	VolP	Telephone	Maintenance	
Web Port Close	Version Information						
Version Information	Model	Tormation		KX-UT	670		
Network Status	OS Ver	sion		2.2			
VoiP Status	Firmware Version			01.072			

3. Now select "Reset to Defaults" on the left navigation menu.

Panasonic								
KX-UT670	Status	Network	System	VoIP	Telephone	Maintenance		
Web Port Close			Firmwa	re Mair	ntenance			
Maintenance	Firmware	Maintenance	1					
Firmware Maintenance	Enable F	Firmware Upd	late 💿	Yes 🔾 N	D			
Reset to Defaults Restart	Firmware File URL			http://10.10.0.1:2004/panasonic/2/UT670.bin				
				Save	Cancel			

4. Finally click the "OK" button to complete the reset.

# Panasonic KX-UT670 Status Network System VolP Telephone Maintenance Web Port Close Reset to Defaults Reset to Defaults Maintenance Reset Web Data The Web data for this unit will be reset to it's default values when you click [Reset Web Settings]. Provisioning Maintenance Reset Web Settings Reset to Defaults Reset Web Settings



# (920) 886-8130

http://schmoozecom.com