

	AASTRA	6739i
	C 1 John Doe	• Thu Feb 23 2:25pm
	Park	Intercom
	DND John Doe Ext. 4009	Day-Night
	Follow-Me	MagicButton
	Presence Status: Not Set	ACDAgents
	Tr-Vmail	•••
	Options Hold Redial Goodby	ye Messages
	Callers 1 2 ABC 3 DEF Directory	Line 3
E	4 GHI 5 JKL 6 MNO Services	Line 2
E	Conf.	Line 1
	Transfer Transfer Mute	Speaker/ Headset



Chapters

- Reset to Factory Defaults
- How to Find the IP Address and MAC Address

How to Set the Configuration Server

Reset to Factory Defaults

Quick Steps

- 1. Select the Options button
- 2. Select the Advanced Menu option



3. Enter the admin password. Default is 22222



4. Select the Reset Menu option



5. Select the Factory Default Menu option



How to Find the IP Address and MAC Address

Quick Steps

- 1. Select the Options button
- 2. Select the Status Menu option



3. Select the Network Menu option



4. You will now be shown the IP Address of the phone.

Network		Mon Jun 21 12:22pm
IP Address	10.4.0.25	
MAC Address	00-08-5D-11-D1-2F	
LAN Port	100/Full (Auto)	
PC Port	Link Down	
←		↓

How to Set the Configuration Server

Quick Steps

- 1. Select the Options button
- 2. Select the Advanced Menu option



3. Enter the admin password. Default is 22222



4. Select the Cfg. Ser. Menu option



5. Select the TFTP box.

Cfg. Svr.		ľ	Mon Jun 21 12:22pm
Download Protocol	TFTP		
	TFTP		
	FTP		
	нттр		
	HTTPS		
÷			•

6. Define the Primary Server Address to your PBX. Generally this would be IP ADDRESS such as 10.10.0.1 in our example.

ТЕТР		ľ	Mon Jun 21 12:22pm
Primary Server	10.10.0.1		
PRI TFTP Path			
Use Alt TFTP	No		
Alternate Server	0.0.0.0		
Alt TFTP Path			
←			•



(920) 886-8130

http://schmoozecom.com